Solid shaft with clamping or synchro flange SIL2 certified

Overview

- Encoder with solid shaft ø10 mm or ø6 mm
- Max. 2500 pulses per revolution
- Optical sensing method
- Clamping or synchro flange
- High rotation speed up to 10000 rpm
- Compact design
- For safety-relevant applications in compliance with SIL2 (Safety Integrity Level 2)



Technical data	
Technical data - electrical ra	atings
Voltage supply	24 VDC +20/-50 %
Reverse polarity protection	Yes
Consumption w/o load	≤30 mA
Pulses per revolution	1000 2500
Reference signal	Zero pulse 70720° electr.
Sensing method	Optical
Output frequency	≤150 kHz
Output signals	A 90° B + inverted
Output stages	Linedriver/RS422 Push-pull short-circuit proof
Safety operating figures	Encoder operating life: 20 years PFH: 1.16E-08 1/h SFF: >90 %
Interference immunity	EN 61000-6-2 IEC 61326-3-1
Emitted interference	EN 61000-6-4
Approval	UL approval / E63076 SIL2 approval according to EN 61508
Technical data - mechanica	l design
Size (flange)	ø58 mm

Technical data - mechanic	al design
Shaft type	ø6 mm solid shaft (synchro flange) ø10 mm solid shaft (clamping flange)
Admitted shaft load	≤20 N axial ≤40 N radial
Flange	Clamping or synchro flange
Protection EN 60529	IP 54 (without shaft seal) IP 65 (with shaft seal)
Operating speed	≤10000 rpm
Starting torque	≤0.015 Nm (+25 °C, IP 54) ≤0.03 Nm (+25 °C, IP 65)
Rotor moment of inertia	14.5 gcm²
Material	Housing: aluminium Flange: aluminium
Operating temperature	-25+85 °C
Relative humidity	95 % non-condensing
Resistance	EN 60068-2-6 Vibration 10 g, 16-2000 Hz EN 60068-2-27 Shock 100 g, 6 ms
Connection	Flange connector M12, 8-pin Flange connector M23, 12-pin
Weight approx.	250 a

Optional

Additional zero pulse (not safety related)

Solid shaft with clamping or synchro flange SIL2 certified

Functional safety remarks

The safety function in the master PLC must detect the following events in order to uncover dangerous errors and, in case of error, actuate appropriate safety precautions:

Non-equivalence Monitoring

The non-inverted and inverted signal lines of each safety track (A+ vs. A- and B+ vs. B-) must have non-equivalent signal levels at all times. In state transition, very short periods of time (some microseconds) are permissible in which both lines have same logical signal level. A dangerous error occurs when this short period of time is exceeded.

Line break detection

Make sure none of the signal cables (A+, A-, B+, B-) is high-impedant. The encoder will utilize the high-impedant status of the safety tracks (A+, A-, B+, B-) to output an error message.

Safe rotational speed

In the event of a predefined speed limit, the master control will require identical speed frequencies on both safety tracks. If not, it is a fatal error

Safe rotational direction

The phase shift of the safety relevant incremental signals (A+ vs. B+ and A- vs. B-) has to be monitored. A dangerous error occurs when exceeding the given tolerances. Compliance to the defined rotational direction has to be monitored as well.


Safe stop

In case of missing state changes in at least one of the signals (A+, A-, B+, B-), the customer has to ensure shaft standstill by means of a second, independent safety precaution within an acceptable amount of time depending on the facility.

Zero pulse as well as the test output are not part of the SIL2 approval and must not be used to fulfill safety functions.

Terminal assignm	nent
------------------	------

Flange connector M23						
Pin	Assignment without zero pulse	Assignment with zero pulse				
1	B-	B-				
2	_	_				
3	Test Out	Test Out				
4	_	Zero pulse				
5	A+	A+				
6	A-	A-				
7	_	_				
8	B+	B+				
9	_	_				
10	GNDB	GNDB				
11	_	n.c. ¹⁾				
12	UB	UB				



Please use cores twisted in pairs (for example A+ / A-) for extension cables of more than 10 m length.

¹⁾ Do not use. Pin is internally assigned and must not be connected externally.

Terminal assignment


Flange connector M12 Pin Assignment without zero pulse	
1	A+
2	B+
3	A-
4	B-
5	-
6	Test Out
7	GNDB
8	UB





Please use cores twisted in pairs (for example A+ / A-) for extension cables of more than 10 m length.

Output signals

Clockwise rotating direction when looking at flange.








Solid shaft with clamping or synchro flange SIL2 certified

Trigger level	
Outputs	Linedriver RS422
Output level High	>2.5 V (I = -20 mA)
Output level Low	<0.5 V (I = 20 mA)
Load High	<20 mA
oad Low <20 mA	
Outputs	Push-pull short-circuit proof
Output level High	>UB -3 V (I = -20 mA)
Output level Low	<0.5 V (I = 20 mA)
Load High	<20 mA
Load Low	<20 mA


Solid shaft with clamping or synchro flange SIL2 certified


Dimensions 48 ±0.1 57 10 20 46 10 20 46 10 20 M4x7 M3x7 M3

Clamping flange, flange connector M23



Clamping flange, flange connector M12





Connector dimensions M23



Solid shaft with clamping or synchro flange SIL2 certified

Ordering reference	EU 5500	0 "						
Down down d	EIL576S	- S #	##	. #	#	#	. #####	•
Product	EIL576S							
Shaft type	EIL3/05							
Solid shaft		s						
Flange								
Clamping flange, ø36 mm, M3/M4		D						
Synchro flange, ø50 mm, M4		V						
Specification solid shaft		·						
ø6 x 10 mm, with flat (synchro flange)			06					
ø10 x 20 mm, with flat (clamping flange)			10					
Protection								
IP 54				4				
IP 65				5				
Connection								
Flange connector M12, 8-pin, axial, male contacts, CCW					Α			
Flange connector M12, 8-pin, radial, male contact, CCW					В			
Flange connector M23, 12-pin, axial, male contacts, CW					С			
Flange connector M23, 12-pin, radial, male contact, CW					Е			
Voltage supply / output stages								
24 VDC / push-pull, 6 channel, with zero pulse ⁽¹⁾						V		
24 VDC / linedriver RS422, 4 channel, without zero pulse						W		
24 VDC / push-pull, 4 channel, without zero pulse						Х		
Pulse number ⁽²⁾								
1000							01000	
1024							01024	
2500							02500	
Operating temperature								
-25+85 °C								

- (1) Version with zero pulse: Only with connector M23, 24 VDC / push-pull and 1024 pulses (zero pulse not safety related). (2) Other pulse numbers on request.

Accessories	
Mounting access	ories
10117669	Eccentric fixing, single (Z 119.006)
10141255	Adaptor plate for clamping flange for modification into synchro flange (Z 119.013)
10117667	Mounting adaptor for encoders with synchro flange (Z 119.015)
10125051	Mounting adaptor for encoders with clamping flange (M3) (Z 119.017)
11034088	Adaptor plate for clamping flange, mounting by eccentric fixings (order separately) (Z 119.025)
10158124	Bearing flange for encoders with synchro flange (Z 119.035)

Page 5 of 5